

DIMIC12S

DIMIC12 extension for
AUDIOCONTROL12.8



DIMIC12S is an extension unit for the DIMIC12 digital paging station. Per DIMIC12 you can connect up to 7 DIMIC12S expansion units allowing a total of 96 programmable buttons available.

When the DIMIC12S is used with AUDIOCONTROL12.

8 you can allocate buttons to perform actions like opening a door, controlling a sound source, ring a bell or even start a series of commands.

The DIMIC12S has 12 free configurable selection buttons and status LEDs.

TECHNICAL SPECIFICATIONS

active	Yes	buttons	12 programmable
indicator	1 per button	zones	12 (up to 96)
connector	Flat Cable	power type	Powered from DIMIC12
width in mm	110	height in mm	58
depth in mm	240	cut-out dimensions in mm	85 x 230
supported main unit	AUDIOCONTROL12.8	Net weight product (kg)	0,34

MORE PICTURES

