

# **PM1122R**

## Wall control panel for PM1122



The PM1122R is a very affordable remote control panel for the PM1122 multifunctional pre-amplifier.

The control panel offers music level control, line source selection and microphone mix level control.

The remote panels are connected to the PM1122 by a standard CAT-5 cable wired according to the T-568B protocol.

The maximum wire length is up to 300m, according to circumstances. You can use one PM1122RL per zone. Mounting screws are included.

#### **TECHNICAL SPECIFICATIONS**

display	No	display backlight	No
supported main unit	PM1122	programmable functions	No
addressing	Hardwired	connector type	RJ45
max. cable length in m	300	power type	Phantom
inputs	No	width in mm	115
height in mm	80	depth in mm	40
weight in gr	165	Net weight product (kg)	0,25



## **MORE PICTURES**







### **ACCESSORIES**





**BBI1**Universal BTicino built-in box 3 modules

 $$\operatorname{\textbf{BB1}}$$  Build on box for remote panel PM1122R and ZONE4R, white